## How to Setup Push Notifications via SCS Pro

The following guide will apply to the SCS Pro App on the iOS App Store or Google Play Store.

Start by opening the App. On the Home screen you will tap on the ... next to the DVR/NVR you want to enable alerts on. Then you will tap on Device Details.



## On the Device Details page you will tap on Multi-channel Alarm Subscription.

<	Device Details		
455	NVR Showroom Online	C	
	Device Model:unknown Device SN:		
Alarm Settings			
Multi-channel /	Alarm Subscription		
Turn on/off Notification switch to control all sub-channel's   message push and storage of phone.			
Devices bound through local binding cannot save alarm messages. Each time you close DMSS App, messages from these device will be lost.			
Disable Alarm	Linkage		
Turn on/off the Disable Alarm Linkage switch to control the linked device's alarm.			
Video Play Setti	ngs		
Stream Setting		>	
Others			
Remote Config	uration	>	
Alarm Output		>	
Other Paramet	ers	>	
	Delete		

Enable the alarm notifications by sliding the switch at the top of the screen.

Select which type of alert you would like to enable below. This example will show motion detection alerts.

<	NVR Showroom	Cle	ear
NVR Showroom			D
After enabling it, or be pushed	nly alarms of the subscril	oed alarm types	s will
Period Settings		00:00-23:59	>
Motion Detection			>
SMD			>
Intrusion Alarm			>
Tripwire Alarm			>
Scene Changing			>
Cam Masking			>
Disk Alarm			>
Face Alarm			>
Temperature Not	within Thresholds		>
Other Alarms			>
	Save		

Select the cameras you want to enable Motion Alerts for by tapping on the **circle** on the right. You can also tap on **Select All** in the top right if you want to enable alerts for all your cameras. Once you have made your selections tap on the back button on the top left.

<	Motion Detection	Select All	
CSP-IPP	TZ12X		
IPC		<b>S</b>	
CSP-IPM	D8-A	<b>e</b>	
CSP-IPM	IC8	<b>&gt;</b>	
IP PTZ C	amera	<b>&gt;</b>	
CSP-IPM	X8-A	0	
Test		0	
CSP-IPP	TZ12X	0	
SOH PTZ		0	
CSP-IPTI	<5	0	
IPC		0	
CSP-CVI	AD8	0	
CSP-CVI	MD2-VF	0	

Tap on **Save** at the bottom of the page.

<	NVR Showroom	Cle	ar
NVR Showroom			
After enabling it, or be pushed	nly alarms of the subscril	oed alarm types	will
Period Settings		00:00-23:59	>
Motion Detection			>
SMD			>
Intrusion Alarm			>
Tripwire Alarm			>
Scene Changing			>
Cam Masking			>
Disk Alarm			>
Face Alarm			>
Temperature Not	within Thresholds		>
Other Alarms			>
	Save		

You will now be receiving alerts on your mobile device. You may need to alter your SCS Pro App settings inside of your phone or tablet to allow notifications.