

1. Locate the serial number of your NVR or DVR. The serial number can be found at the following locations:


- On the underside or side of the unit



- Inside the Network Settings. Under Main Menu->Settings->Network->P2P



- On the system interface under Main Menu->Info->System->Version




Once you have located your Serial Number (SN) we can now launch SmartPSS to begin configuration.

SmartPSS can be found on your desktop once installed.




Launch SmartPSS from your desktop by double clicking the icon

3. Once SmartPSS is running click on “Devices”.



4. Click on “Manual Add”



### 5. Input the following:

- **Device Name:** (Any Name)
- **Register Mode:** Change to SN
- **SN:** (Your Device's Serial Number)
  - **Group Name:** (Default Group)
    - **User Name:** admin
- **Password:** admin (Your DVR/NVR Password)

Manual Add X

---

Input Info

Device Name:

Register Mode:  ▼

SN:

Port:

Group Name:  ▼

User Name:

Password:

---

Device Details

Device SN:

Type:  ▼

Video Input:

Video Output:

Alarm Input:

Alarm Output:

**Once all of your information is entered. Click “Get Info”. Once the device details have been automatically entered, click “Add”.**

Manual Add X

Input Info

Device Name: My NVR

Register Mode: SN (For device with P2P functi

SN: 1A02A6EPAYA9E3C

Port: 37777

Group Name: Default Group

User Name: admin

Password: •••••

**Get Info**

Device Details

Device SN: 1A02A6EPAYA9E3C

Type: NVR

Video Input: 1

Video Output: 0

Alarm Input: 0

Alarm Output: 0

Save and Continue   Add   Cancel

**After a few moments, SmartPSS will connect to the NVR and display as, "Online"**

SmartPSS Professional Surveillance System




HOME PAGE DEVICES ADD

Online Devices: Device Network Section: 172.16.16.0 — 172.16.16.255 Search

All	IP	Type	Mac	Port

Refresh Add Clear

All Devices:1 Online:1

All	Name	Type	IP/Domain Name	Port	Channel No.	Status	SN	Operation
<input checked="" type="checkbox"/>	My NVR	NVR	1A02A6EPAYA9E3C	37777	4/0/0/0	Online	1A02A6EPAYA...	  

Manual Add Delete Import Export Status

**Your Device has now been added to SmartPSS.**